

## P8H61-M LX3 PLUS

### DDR3 1067 Qualified Vendors List (QVL)

Vendors	Part No.	Size	SS/DS	Chip Brand	Chip NO.	Timing	Voltage	ocket support (O	
								1 DIMM	2 DIMM
<b>Crucial</b>	CT12864BA1067.8FF	1GB	SS	Micron	9GF22D9KPT	7	-	●	●
<b>ELPIDA</b>	EBJ10UE8EDF0-AE-F	1GB	SS	ELPIDA	J1108EDSE-DJ-F	-	1.35V(low voltage)	●	●
<b>ELPIDA</b>	EBJ21UE8EDF0-AE-F	2GB	DS	ELPIDA	J1108EDSE-DJ-F	-	1.35V(low voltage)	●	●
<b>KINGSTON</b>	KVR1066D3N7/2G	2GB	DS	ELPIDA	J1108BDSE-DJ-F	7	1.5V	●	●
<b>KINGSTON</b>	KVR1066D3N7/4G	4GB	DS	Hynix	H5TQ2G83AFR	7	1.5V	●	●
<b>Micron</b>	MT16JTF25664AZ-1G1F1	2GB	DS	Micron	9HF22D9KPT	7	-	●	●
<b>Vendor</b>	PartNum.	Size	SS/DS	Chip Brand	ChipNum.	Timing - Dimm	Vol.	0	0

4 DIMM Slots

- **1 DIMM:** Supports one module inserted in any slot as Single-channel memory configuration
- **2 DIMM:** Supports 2 modules inserted into both the **blue** or **black** slots as two pairs of Dual-channel memory configuratio

-When installing total memory of 4GB capacity or more, Windows 32-bit operation system may only recognize less than 3GB. Hence, a total installed memory of less than 3GB is recommended.

-It is recommended to install the memory modules from the slots for better overclocking capability.

-The default DIMM frequency depends on its Serial Presence Detect (SPD), which is the standard way of accessing information from a memory module. Under the default state, some memory modules for overclocking may operate at a lower frequency than the vendor-marked value.



## P8H61-M LX3 PLUS

### DDR3 1333 Qualified Vendors List (QVL)

Vendors	Part No.	Size	SS/DS	Chip Brand	Chip NO.	Timing	Voltage	Socket support (O)	
								1 DIMM	2 DIMM
A-DATA	AM2U139C2P1	2GB	SS	ADATA	3CCD-1509A EL1127T	-	-	•	•
A-DATA	AM2U139C4P2	4GB	DS	ADATA	3CCD-1509A EL1127T	-	-	•	•
A-DATA	SU3U1333W8G9-B	8GB	DS	ELPIDA	J4208BASE-DJ-F	-	-	•	•
Apacer	AU02GFA33C9NBGC	2GB	DS	Apacer	AM5D5808APQSBG	-	-	•	•
CORSAIR	TR3X3G1333C9 G	3GB	SS	-	-	9-9-9-24	1.50V	•	•
CORSAIR	TW3X4G1333C9D G	4GB	DS	-	-	9-9-9-24	1.50V	•	•
CORSAIR	CMX4GX3M1A1333C9	4GB	DS	-	-	9-9-9-24	1.50V	•	•
Crucial	BL25664BN1337.16FF (XMP)	2GB	DS	-	-	7-7-7-24	1.65V	•	•
ELPIDA	EBJ10UE8EDF0-DJ-F	1GB	SS	ELPIDA	J1108EDSE-DJ-F	-	1.35V(low voltage)	•	•
ELPIDA	EBJ21UE8EDF0-DJ-F	2GB	DS	ELPIDA	J1108EDSE-DJ-F	-	1.35V(low voltage)	•	•
G.SKILL	F3-10600CL8D-2GBHK(XMP)	1GB	SS	G.SKILL	-	-	-	•	•
G.SKILL	F3-10600CL9D-2GBNQ	2GB	SS	-	-	9-9-9-24	1.5V	•	•
G.SKILL	F3-10666CL8D-4GBECO(XMP)	4GB	DS	-	-	8-8-8-24	XMP 1.35V	•	•
GEIL	GG34GB1333C9DC	4GB	DS	GEIL	GL1L128M88BA12N	9-9-9-24	1.3V(low voltage)	•	•
GEIL	GVP34GB1333C7DC	4GB	DS	-	-	7-7-7-24	1.5V	•	•
KINGMAX	FLFD45F-B8KL9 NAES	1GB	SS	KINGMAX	KKB8FNWBFGNX-27A	-	-	•	•
KINGMAX	FLFF65F-C8KL9 NEES	4GB	DS	KINGMAX	KFC8FNLXF-DXX-15A	-	-	•	•
KINGMAX	FLFF65F-C8KM9 NEES	4GB	DS	KINGMAX	KFC8FNMXF-BXX-15A	-	-	•	•
KINGSTON	KVR1333D3N9/2G(矮版)	2GB	SS	Hynix	H5TQ2G83AFRH9C	9	-	•	•
KINGSTON	KHX1333C9D3UK2/4GX(XMP)	4GB	DS	-	-	9	XMP 1.25V	•	•
KINGSTON	KVR1333D3N9/4G(矮版)	4GB	DS	ELPIDA	J2108BCSE-DJ-F	-	1.5V	•	•
KINGSTON	KVR1333D3N9/4G	4GB	DS	KTC	D2568JENCNGD9U	-	1.5V	•	•
Micron	MT8JTF25664AZ-1G4M1	2GB	SS	MICRON	IJM22 D9PFJ	-	-	•	•
Micron	MT16JTF51264AZ-1G4D1	4GB	DS	Micron	OLD22D9LGK	-	-	•	•
NANYA	NT4GC64B8HG0NF-CG	4GB	DS	NANYA	NT5CB256M8GN-CG	-	-	•	•
Super	W1333UA1GH	1GB	SS	Hynix	H5TQ1G83TFR	9	-	•	•
Super	W1333UB4GS	4GB	DS	SAMSUNG	K4B2G0846C	-	-	•	•
Super	W1333UX6GM	6GB(3x 2GB)	DS	Micron	0BF27D9KPT	9-9-9-24	1.5V	•	•
Transcend	JM1333KLN-2G	2GB	SS	Micron	0YD77D9LGK	-	-	•	•
Transcend	JM1333KLU-2G	2GB	DS	Transcend	TK243PDF3	-	-	•	•
Vendor	PartNum.	Size	SS/DS	Chip Brand	ChipNum.	Timing	Vol.	0	0

#### 4 DIMM Slots

- **1 DIMM:** Supports one module inserted in any slot as Single-channel memory configuration
- **2 DIMM:** Supports 2 modules inserted into both the [blue](#) or [black](#) slots as two pairs of Dual-channel memory configuration

-When installing total memory of 4GB capacity or more, Windows 32-bit operation system may only recognize less than 3GB. Hence, a total installed memory of less than 3GB -It is recommended to install the memory modules from the slots for better overclocking capability.

-The default DIMM frequency depends on its Serial Presence Detect (SPD), which is the standard way of accessing information from a memory module. Under the default state, some memory modules for overclocking may operate at a lower frequency than the vendor-marked value.

is recommende