

# B150M-C

## DDR4 2133 Qualified Vendors List (QVL)

Vendors	Part No.	Size	SS/DS	Chip Brand	Chip NO.	Timing	Voltage	DIMM socket support (Optional)		
								1 DIMM	2 DIMM	4 DIMM
<b>SAMSUNG</b>	M378A5143DB0--CPB	4G	SS	SEC 428 BCPB	K4A4G085WD	13-13-13-33	1.5V		•	•
<b>SAMSUNG</b>	M378A1G43DB0--CPB	8G	DS	SEC 428 BCPB	K4A4G085WD	13-13-13-33	1.5V		•	•
<b>G.SKILL</b>	F4-2133C15Q-32GRK	8G	DS	N/A	Heat-Sink Package	15-15-15-35	1.2V		•	•
<b>GLOWAY</b>	PC4-17000	4G	SS	N/A	Heat-Sink Package	15-15-15-35	1.2V		•	•
<b>KINGSTON</b>	HX421C13PBK4/16	4G	SS	N/A	Heat-Sink Package		1.2V		•	•
<b>KINGSTON</b>	HX421C14FB/8	8G	DS	N/A	Heat-Sink Package	14-14-14-35	1.2V		•	•
<b>KINGSTON</b>	HX421C14FBK4/32	8G	DS	N/A	Heat-Sink Package		1.2V		•	•
<b>PANRAM</b>	PUD42133C138G4NJW	8G	DS	N/A	Heat-Sink Package	13-13-13-35	1.2V		•	•
<b>PANRAM</b>	PUD42133C134G4NJW	4G	SS	N/A	Heat-Sink Package	13-13-13-35	1.2V		•	•
<b>CORSAIR</b>	CMK16GX4M4A2133C15	4G	SS	N/A	Heat-Sink Package	15-15-15-36	1.2V		•	•
<b>CORSAIR</b>	CMV4GX4M1A2133C15	4G	SS	N/A	4GA72Z9RGR	13-13-34-33	1.5V		•	•
<b>CORSAIR</b>	CMV8GX4M1A2133C15	8G	DS	SEC 446 BCPB	K4A4G085WD	13-13-13-33	1.5V		•	•
<b>CRUCIAL</b>	MTA8ATF51264AZ-2G1A1	4G	SS	MICRON	4QA77D9RCQ	13-13-13-33	1.2V		•	•
<b>TEAM</b>	TED44GM2133C15BK	4G	DS	SEC 443 BCBP	K4A4G085WD	15-15-15-36	1.2V		•	•
<b>TEAM</b>	TED48GM2133C15BK	8G	SS	SEC 437BCBP	K4A4G085WD	15-15-15-36	1.2V		•	
<b>APACER</b>	78.C1GM3.AF10B	8G	DS	SK HYNIX	H5AN4G8NMFR	14-14-14-33	1.5V		•	•
<b>APACER</b>	AU04GGB13CDTBGC	4G	SS	SK HYNIX	H5AN4G8NMFR	14-14-14-33	1.5V		•	
<b>TEKISM</b>	T4U2133B8G15-SAD	8G	DS	SEC 446 BCPB	K4A4G085WD				•	•
<b>KINGSTON</b>	KVR21N15D8/8	8G	DS	SK HYNIX	H5AN4G8NMFR		1.2V		•	•

### 4 DIMM Slots

- **1 DIMM:** Supports one module inserted in any slot as Single-channel memory configuration
- **2 DIMM:** Supports one pair of modules inserted into either the **gray** slots or the **black** slots as one pair of Dual-channel memory configuration
- **4 DIMM:** Supports 4 modules inserted into both the **gray** and **black** slots as two pairs of Dual-channel memory configuration

-When installing total memory of 4GB capacity or more, Windows 32-bit operation system may only recognize less than 3GB. Hence, a total installed memory of less than 3GB is recommended.

-It is recommended to install the memory modules from the slots for better overclocking capability.

-The default DIMM frequency depends on its Serial Presence Detect (SPD), which is the standard way of accessing information from a memory module. Under the default state, some memory modules for overclocking may operate at a lower frequency than the vendor-marked value.

# B150M-C

## DDR4 2400 Qualified Vendors List (QVL)

Vendors	Part No.	Size	SS/DS	Chip Brand	Chip NO.	Timing	Voltage	DIMM socket support (Optional)		
								1 DIMM	2 DIMM	4 DIMM
ADATA	AX4U2400W8G16-DRZ	8G	DS	N/A	Heat-Sink Package	16-16-16	1.2V	•	•	
G.SKILL	F4-2400C15Q-32GRB	8G	DS	N/A	Heat-Sink Package	15-15-15-35	1.2V	•	•	
G.SKILL	F4-2400C14Q2-128GRK	16G	DS	N/A	Heat-Sink Package	14-14-14-34	1.2V	•	•	
PATRIOT	PX416G240C5QK	4G	SS	N/A	Heat-Sink Package	15-15-15-35	1.2V	•	•	
GLOWAY	PC4-19200	4G	SS	GLOWAY	512X8DDR4	16-16-16-35	1.2V	•	•	
TEAM	TED44GM2400C16BK	4G	SS	SEC 437 BCPB	K4A4G085WD	16-16-16-39	1.2V	•	•	
TEAM	TED48GM2400C16BK	8G	DS	SEC 443 BCPB	K4A4G085WD	16-16-16-39	1.2V	•	•	
PANRAM	PUD42400C154G4NJW	4G	SS	N/A	Heat-Sink Package	15-15-15-35	1.2V	•	•	
PANRAM	PUD42400C158G4NJW	8G	DS	N/A	Heat-Sink Package	15-15-15-35	1.2V	•	•	
CORSAIR	CMK32GX4M4A2400C14	8G	DS	N/A	Heat-Sink Package	14-16-16-31	1.2V	•	•	
CRUCIAL	BLS4K4G4D240FSA	4G	SS	N/A	Heat-Sink Package	16-16-16-39	1.2V	•	•	
ADATA	AX4U2400W4G16-DRZ	4G	SS	N/A	Heat-Sink Package	16-16-16	1.2V	•	•	
GEIL	GPR416GB2400C15QC	4G	SS	N/A	Heat-Sink Package	15-15-15-35	1.2V	•	•	
MUSHKIN	997199F	8G	DS	N/A	Heat-Sink Package	15-15-15-35-50	1.2V	•	•	
KINGSTON	HX424C15FBK4/32	8G	DS	N/A	Heat-Sink Package	15-15-15-35-57	1.2V	•	•	
KINGSTON	HX424C15FBK4/16	4G	SS	N/A	Heat-Sink Package		1.2V	•	•	
APACER	78.C1GMA.AF30B	8G	DS	SK HYNIX	H5AN4G8NMFR	16-16-16-36	1.2V	•	•	
APACER	78.B1GMA.AF20B	4G	SS	SK HYNIX	H5AN4G8NMFR	16-16-16-36	1.2V	•	•	

### 4 DIMM Slots

- **1 DIMM:** Supports one module inserted in any slot as Single-channel memory configuration
- **2 DIMM:** Supports one pair of modules inserted into either the gray slots or the **black** slots as one pair of Dual-channel memory configuration
- **4 DIMM:** Supports 4 modules inserted into both the **gray** and **black** slots as two pairs of Dual-channel memory configuration

-When installing total memory of 4GB capacity or more, Windows 32-bit operation system may only recognize less than 3GB. Hence, a total installed memory of less than 3GB is recommended.

-It is recommended to install the memory modules from the slots for better overclocking capability.

-The default DIMM frequency depends on its Serial Presence Detect (SPD), which is the standard way of accessing information from a memory module. Under the default state, some memory modules for overclocking may operate at a lower frequency than the vendor-marked value.

# B150M-C

## DDR4 2666 Qualified Vendors List (QVL)

Vendors	Part No.	Size	SS/DS	Chip Brand	Chip NO.	Timing	Voltage	DIMM socket support (Optional)		
								1 DIMM	2 DIMM	4 DIMM
<b>G.SKILL</b>	F4-2666C15Q-16GRR	4G	SS	N/A	Heat-Sink Package	15-15-15-35	1.2V		•	•
<b>TEAM</b>	TCD44G2666C15ABK	4G	SS	SEC 443 BCPB	K4A4G085WD	15-15-15-35	1.2V		•	•

### 4 DIMM Slots

- **1 DIMM:** Supports one module inserted in any slot as Single-channel memory configuration
- **2 DIMM:** Supports one pair of modules inserted into either the **gray** slots or the **black** slots as one pair of Dual-channel memory configuration
- **4 DIMM:** Supports 4 modules inserted into both the **gray** and **black** slots as two pairs of Dual-channel memory configuration

-When installing total memory of 4GB capacity or more, Windows 32-bit operation system may only recognize less than 3GB. Hence, a total installed memory of less than 3GB is recommended.

-It is recommended to install the memory modules from the **gray** slots for better overclocking capability.

-The default DIMM frequency depends on its Serial Presence Detect (SPD), which is the standard way of accessing information from a memory module. Under the default state, some memory modules for overclocking may operate at a lower frequency than the vendor-marked value.

# B150M-C

## DDR4 2800 Qualified Vendors List (QVL)

Vendors	Part No.	Size	SS/DS	Chip Brand	Chip NO.	Timing	Voltage	DIMM socket support (Optional)		
								1 DIMM	2 DIMM	4 DIMM
PANRAM	PUD42800C164G4NJW	4G	SS	N/A	Heat-Sink Package	16-18-18-36	1.25V	•	•	
MUSHKIN	994207F	4G	SS	N/A	Heat-Sink Package	16-16-16-36-52	1.2V	•	•	

### 4 DIMM Slots

- **1 DIMM:** Supports one module inserted in any slot as Single-channel memory configuration
- **2 DIMM:** Supports one pair of modules inserted into either the [gray](#) slots or the [black](#) slots as one pair of Dual-channel memory configuration
- **4 DIMM:** Supports 4 modules inserted into both the [gray](#) and [black](#) slots as two pairs of Dual-channel memory configuration

-When installing total memory of 4GB capacity or more, Windows 32-bit operation system may only recognize less than 3GB. Hence, a total installed memory of less than 3GB is recommended.

-It is recommended to install the memory modules from the [gray](#) slots for better overclocking capability.

-The default DIMM frequency depends on its Serial Presence Detect (SPD), which is the standard way of accessing information from a memory module. Under the default state, some memory modules for overclocking may operate at a lower frequency than the vendor-marked value.