

ASUS Win Flash

User's Guide



Contents

Chapter 1	ASUS Win Flash1	1
1.1	Introduction	1
1.2	How to upgrade BIOS	1



Chapter 1 ASUS Win Flash

1.1 Introduction

ASUS Win Flash is a tool to update BIOS in Windows.

Please verify the exact model and download the latest BIOS file for your Notebook from ASUS Download Site.

Please ensure that you have installed ASUS Win Flash Utility before using update procedure. You may install the program via Driver & Utility CD if you cannot find the program from **Start -> All Programs->ASUS Utility.**

1.2 How to upgrade BIOS

1. Click Start \ All Programs \ ASUS Utility \ WINFLASH \ WINFLASH





Flash BIOS Program for Win98SE/WinME/Win2K/WinXP						
1	This Program will Updata your BIOS. Only update your BIOS if you have problems with your Notebook PC and you know that the new BIOS revision will solve your problems (read the BIOS release information provided on the download site before using). Careless updating can result in your Notebook PC having more problems! OK					

2. Select and open the updated BIOS image file

Open			? 🛛
Look in: [My Documents	-	• 🖬 🖬
My eBooks My Music My Picture	s A.ROM		
File name:	A2D0205A		Open
Files of type:	× ×	<u>.</u>	Cancel

3. Please confirm the loaded BIOS information as displayed in the following image



For Wind	ows	
	BIOS ROM Information ROM Type: SST 49L F004A Model: VV5A Version: BIOS Revision 0205	Check out
	Date: 06/08/05 BIOS Image Information File Name:	 Model Version
Erase ROM Flash ROM Verify ROM	Message BIOS image format is correct, you can press [Flash] button to update BIOS ROM	Follow this message and flash your BIOS easily
	Flash Exit	

4. Press **Flash** to initialize BIOS updating procedure

			BIOS	
or Wind	ows			
A	BIOS ROM In ROM Type: Model: Version: Date:	formation SST 39SF040 A2D BIOS Revision 03/17/04	0204	
	BIOS Image I File Name: Model: Version: Date:	nformation C:VDocuments A2D BIOS Revision 03/31/04	and Settings\David\My 0205	
Rose ROM	10	10%		
Flash ROM 78		8%	some seconds to complete.	
Citry Hom				

5. Press "Exit" when procedure completes



			BIOS
or Wind	ows		
A	BIOS ROM In ROM Type: Model: Version: Date:	formation SST 39SF040 A2D BIOS Revision 03/31/04	0205
	BIOS Image I File Name: Model: Version: Date:	nformation C: Vocuments A2D BIOS Revision 03/31/04	and Settings\David\My 0205
rase ROM	10	0%	-Message
Flash ROM	100%		reboot the system. And CMOS will automatically load default
erify ROM	100%		Anonatoni, ford dorddir
		Flash	Exit

6. Please reboot the system



Assuming that you have successfully flashed the BIOS file, press F2 to enter BIOS setup page when ASUS white logo appears during system Boot-up procedure

 After entering BIOS setup page, please go to Exit sub-menu and choose "Load Optimal Defaults". Then click "Save and Exit" and reboot system again. The BIOS flash procedure is now completed



BIOS SETUP UTILITY							
Main	Advanced	Display	Security	Power	Boot	Exit	
Exit Options					Exit system setup		
Save Ch Discard Load Op Load Fa	anges and Ex Changes and Changes timal Defaul ilsafe Defau	iit Exit 			after change F10 ke for th for th ti Enter F1 F9 F10 ESC	saving the ES. By can be used his operation. Select Screen Select Iten Go to Sub Screen General Help Load Defaults Save and Exit Exit	
	v02.33 (0	Copyright	1985-2002, Am	erican Me	gatrends	s, Inc.	