

- How to update PLX-8747 firmware:

- 1) Extract attached file to a bootable USB flash disk.
- 2) Execute the file in DOS environment.
- 3) Go to the file path of 8747/
- 4) Execute '8747.BAT'.

```
C:\8747>8747.bat
C:\8747>program.bat 8747CA.bin
Selected: 8747 10b5 [b:01 s:00 f:0]

Load EEPROM file..... Ok (268B)
Program EEPROM..... Ok
Calculate & update CRC.... Ok (CRC=413021FB)
-- Complete (0.16 sec) --
Program EEPROM: Ok
Selected: 8747 10b5 [b:01 s:00 f:0]

Get EEPROM data size.. Ok (272B inc 32-bit CRC)
Read EEPROM data..... Ok
Write data to file.... Ok (temp.bin)
-- Complete (0.05 sec) --
C:\8747>_
```

- 5) Press power button to power off the system for a while then power it on, the firmware update is finished.